
Complete List

of

RADIO LA

RECEIVERS

•

1925-1938

•

Amalgamated  **Wireless**
(Australasia) Ltd

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1925	4	Table	T.R.F.	—	4-UV199	4V., Battery-Operated	Magnetic
"	C25	Table	Superhet.	50 K.C.	6-UV199	6V., Battery-Operated	Magnetic
"	"Sheraton" C25	Console	Superhet.	50 K.C.	6-UV199	6V., Battery-Operated	Magnetic
"	"Super Sports" C25	Portable	Superhet.	50 K.C.	6-UV199	6V., Battery-Operated	Magnetic
1926	C26	Table	Superhet.	50 K.C.	6-UX199	6V., Battery-Operated	Magnetic
"	C26	Console	Superhet.	50 K.C.	6-UX199	6V., Battery-Operated	Magnetic
"	4A/C28	Table	T.R.F.	—	4-UX199	4V., Battery-Operated	Magnetic
"	5A/C29	Table	T.R.F.	—	3-UX199, 2-P410	5V., Battery-Operated	Magnetic
"	3A	Table	T.R.F.	—	3-UX199	3V., Battery-Operated	Magnetic
1927	C33	Portable	Superhet.	50 K.C.	6-UX199	6V., Battery-Operated	Magnetic
"	"Standard" C38	Table	Superhet.	50 K.C.	4-UX199, 1-L410, 1-P410	6V., Battery-Operated	Magnetic
"	"Senior" C39	Table	Superhet.	50 K.C.	4-UX199, 1-L410, 1-P410	6V., Battery-Operated	Magnetic
"	"Super Eight" C40	Console	Superhet.	50 K.C.	6-UX199, 2-P410	8V., Battery-Operated	Magnetic
"	4C/C42	Table	T.R.F.	—	2-UX199, 2-P410	4V., Battery-Operated	Magnetic
"	4C/C47	Portable	T.R.F. (Browning Drake)	—	2-L210, 2-P210	4V., Battery-Operated	Magnetic
1928	"Straight Six" C48	Table	T.R.F.	—	5-L410, 1-P410	6V., Battery-Operated	Magnetic
"	"Straight Six" C49	Table	T.R.F.	—	4-26, 1-27, 1-71A, 1-80	6V., A.C. Operated	Magnetic
"	"Screened Six" C50	Console	T.R.F.	—	5-L410, 1-P410	6V., Battery-Operated	Magnetic
"	"Screened Six" C51	Console	T.R.F.	—	4-26, 1-27, 1-71A, 1-80	6V., A.C. Operated	Magnetic
1929	"Electric 3" C53	Table	T.R.F.	—	1-27, 1-26, 1-112A, 1-80	3V., A.C. Operated	Magnetic
"	"Batt. Six" C54	Table	T.R.F.	—	5-L410, 1-P410	6V., Battery-Operated	Magnetic
"	"Batt. Six" C54	Console	T.R.F.	—	5-L410, 1-P410	6V., Battery-Operated	Magnetic
"	"Electric 7" C55	Table	T.R.F.	—	5-26, 1-27, 1-71A, 1-80	7V., A.C. Operated	Magnetic

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1929	"Electric 7" C55	Console	T.R.F.	—	5-26, 1-27, 1-71A, 1-80	7V., A.C. Operated	Magnetic
"	"Duoforte" C56	Radiogram	T.R.F.	—	5-26, 1-27, 2-71A, 1-80	8V., Phono-Radio, A.C. Operated, P.P. Output	E.M. 500 ohms
"	"Batt. 7" C57	Table	T.R.F.	—	6-L410, 1-P410	7V., Battery-Operated	Magnetic
"	"Batt. 7" C57	Console	T.R.F.	—	6-L410, 1-P410	7V., Battery-Operated	Magnetic
"	"Duoforte" C58	Radiogram	T.R.F.	—	6-26, 1-27, 2-45, 1-80	9V., Phono-Radio, A.C. Operated, P.P. Output	Magnavox Type 405
1930	40/C62	Table	T.R.F.	—	2-24, 1-27, 1-71A, 1-80	4V., A.C. Operated	Magnetic
"	40/C62A	Console	T.R.F.	—	2-24, 1-47, 1-71A, 1-80	4V., A.C. Operated	Magnetic
"	50/C63	Table	T.R.F.	—	5-L410, 1-P410	6V., Battery-Operated	Magnetic
"	50/C63A	Table	T.R.F.	—	5-L410, 1-P410	6V., Battery-Operated	Magnetic
"	70/C64	Table	T.R.F.	—	5-27, 1-71A, 1-80	6V., A.C. Operated	Magnetic
"	70/C64A	Table	T.R.F.	—	5-27, 1-71A, 1-80	6V., A.C. Operated	Magnetic
"	80/C65	Table	T.R.F.	—	3-22, 2-L410, 1-P410	6V., Battery-Operated	Magnetic
"	80/C65A	Table	T.R.F.	—	3-22, 2-L410, 1-P410	6V., Battery-Operated	Magnetic
"	90/C66	Table	T.R.F.	—	4-24, 1-27, 1-45, 1-80	6V., A.C. Operated	E.M. 7500 ohms
"	90/C66A	Console	T.R.F.	—	4-24, 1-27, 1-45, 1-80	6V., A.C. Operated	E.M. 7500 ohms
"	"Duoforte" 40/C67	Radiogram	T.R.F.	—	2-24, 1-27, 1-45, 1-80	4V., Phono-Radio, A.C. Operated	E.M. 7500 ohms
"	"Duoforte" 90/C68	Radiogram	T.R.F.	—	4-24, 2-27, 2-45, 1-80*	8V., Phono-Radio, A.C. Operated, Push-Pull Output	E.M. 7500 ohms
"	45/C73	Console	T.R.F.	—	3-24, 1-45, 1-80	4V., A.C. Operated	E.M. 7500 ohms
"	"Duoforte" 45/C74	Radiogram	T.R.F.	—	3-24, 1-45, 1-80	4V., Phono-Radio, A.C. Operated	E.M. 7500 ohms
"	34/C76	Mantel	T.R.F.	—	2-24, 1-MHL4, 1-80	3V., A.C. Operated	Magnetic
1931	34E/C77	Console	T.R.F.	—	2-24, 1-45 or 47, 1-80	3V., A.C. Operated	E.M. 2500 ohms
"	45B/C78	Table	T.R.F.	—	3-32, 1-P215	4V., Battery-Operated	Magnetic
"	45E/C79	Console	T.R.F.	—	3-24, 1-45, 1-80	4V., A.C. Operated	E.M. 7500 ohms
"	80B/C82	Table	T.R.F.	—	3-32, 2-L210, 1-P215	6V., Battery-Operated	Magnetic
"	80B/C282A	Console	T.R.F.	—	3-32, 2-L210, 1-P215	6V., Battery-Operated	Magnetic
"	"Duoforte" 45E	Radiogram	T.R.F.	—	3-24, 1-45, 1-80	4V., Phono-Radio, A.C. Operated	E.M. 7500 ohms
"	"Duoforte" 90E/C81	Radiogram	T.R.F.	—	4-24, 1-27, 2-45, 1-80	7V., Phono-Radio, A.C. Operated	E.M. 7500 ohms
1932	"Junior" C87	Console	T.R.F.	—	1-35, 1-24, 1-47, 1-80	3V., A.C. Operated	E.M. 2000 ohms
"	"Radiolette" C87	Mantel	T.R.F.	—	1-35, 1-24, 1-47, 1-80	3V., A.C. Operated	E.M. 2000 ohms

* In late models 2-80 valves were used.

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1932	"Duoforte" 55E/C89	Radiogram	T.R.F.	—	3-35, 1-24, 1-47, 1-80	5V., Phono-Radio, A.C. Operated	E.M. 2000 ohms
"	55E/C89	Console	T.R.F.	—	3-35, 1-24, 1-47, 1-80	5V., A.C. Operated	E.M. 2000 ohms
"	46E/C92	Console	T.R.F.	—	2-35, 1-24, 1-47, 1-80	4V., A.C. Operated	E.M. 2000 ohms
"	55C/C94	Console	T.R.F.	—	3-39, 1-36, 2-38	6V., D.C. Operated with parallel output.	E.M. 4500 ohms
"	55B/C90	Console	T.R.F.	—	3-32, 4-30	7V., Battery-Operated, Push-Pull output	P.M.
1933	110/C104	Mantel	Superhet.	175 K.C.	2-57, 1-58, 1-59, 1-80	4V., A.C. Operated	E.M. 2000 ohms
"	120/C105	Console	Superhet.	175 K.C.	2-57, 1-58, 1-59, 1-80	4V., A.C. Operated	E.M. 2000 ohms
"	130/C106	Console	Superhet.	175 K.C.	3-58, 1-56, 1-55, 1-59, 1-80	6V., A.C. Operated	E.M. 2000 ohms
"	120B/C107	Console	Superhet.	175 K.C.	2-34, 1-32, 3-30	6V., Battery-Operated, Push-Pull output	P.M.
"	130B/C108	Console	Superhet.	175 K.C.	2-34, 2-32, 4-30	8V., Battery-Operated, Push-Pull output	P.M.
"	130DC/C116	Console	Superhet.	175 K.C.	2-78, 1-6A7, 1-77, 1-43	5V., D.C. Operated	E.M. 135 ohms
"	137/C120	Console	Superhet.	175 K.C.	2-58, 1-2A7, 1-2B7, 2-2A5, 1-80	6V., A.C. Operated, Push-Pull output	E.M. 850 ohms
"	136/C132	Console	Superhet.	175 K.C.	2-78, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 2000 ohms
1934					From this year onwards the rectifier is classed as a valve.		
"	"Radiolettes" 24, 34 & 44	Mantel	Superhet.	175 K.C.	1-78, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	24 & 34 E.M. 1000 ohms 44 E.M. 2000 ohms
"	"Radiolettes" 54 & 57	Mantel	Superhet.	175 K.C.	1-78, 1-6A7, 1-6B7, 1-43, 1-12Z3	5V., Universal A.C.-D.C.	E.M. 1000 ohms
"	"Radiolettes" 64 & 67	Mantel	Superhet.	175 K.C.	1-78, 1-6A7, 1-6B7, 1-38	4V., Battery-Operated	P.M.
"	"Radiolettes" 27 & 47	Mantel	Superhet.	175 K.C.	1-78, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	27 E.M. 1000 ohms 47 E.M. 2000 ohms
"	74	Console	Superhet.	175 K.C.	1-78, 1-6A7, 1-6B7, 1-42	4V., Automobile Receiver, vibrator powered	E.M. 100 ohms
"	138	Console	Superhet.	175 K.C.	2-34, 1-1A6, 2-30, 1-19	6V., Battery-Operated, Class "B" output	P.M.
"	139	Console	Superhet.	175 K.C.	2-78, 1-6A7, 1-6B7, 1-42, 1-80	6V., A.C. Operated	E.M. 2000 ohms
"	140	Console	Superhet.	175 K.C.	2-78, 1-6A7, 1-6B7, 1-42, 1-53, 1-80	7V., A.C. Operated, Class "B" output	E.M. 850 ohms
"	240	Console	Superhet.	460 K.C.	3-6D6, 1-6A7, 1-6B7, 1-42, 1-80	7V., A.C. Operated, Three Band	E.M. 2000 ohms
"	141	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 2000 ohms
"	"Radiolettes" 28 & 68	Mantel	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms
"	142	Console	Superhet.	175 K.C.	2-6D6, 1-6A7, 1-6B7, 1-42, 1-80	6V., A.C. Operated	E.M. 2000 ohms

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1934	143	Console	Superhet.	175 K.C.	2-34, 1-1A6, 2-30, 1-19	6V., Battery-Operated, Class "B" output	P.M.
"	144	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-43, 1-12Z3	5V., Universal A.C.-D.C.	E.M. 2000 ohms
"	145	Console	Superhet.	175 K.C.	2-34, 1-1A6, 1-6B7, 1-38	5V., Battery-Operated	P.M.
"	301	Console	Superhet.	460 K.C.	3-6D6, 1-6A7, 1-6B7, 3-42, 1-80	9V., Phono-Radio, A.C. Operated, Three Band, Push-Pull Output	E.M. 2000 ohms
"	"Radiolette" 69	Mantel	Superhet.	175 K.C.	1-34, 1-1A6, 1-6B7, 1-38	4V., Battery-Operated	P.M.
1935	"Radiolettes" 29 & 71	Mantel	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms
"	"Radiolette" 70	Mantel	Superhet.	175 K.C.	1-34, 1-1A6, 1-6B7, 1-38	4V., Battery-Operated	P.M.
"	146	Mantel	Superhet.	175 K.C.	1-1A6, 1-34, 1-32, 1-33	4V., Battery-Operated	P.M.
"	147	Console	Superhet.	175 K.C.	2-34, 1-1A6, 1-6B7, 1-38	5V., Battery-Operated	P.M.
"	148	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-43	4V., Universal A.C.-D.C.	E.M. 2000 ohms
"	72	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-43	4V., D.C. Operated	E.M. 2000 ohms
"	151	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 2000 ohms
"	241	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-42, 1-6B7, 1-80	6V., A.C. Operated, Three Band	E.M. 2000 ohms
"	242	Console	Superhet.	460 K.C.	3-6D6, 1-6A7, 1-6B7, 1-42, 1-80	7V., A.C. Operated, Three Band	E.M. 2000 ohms
"	243	Console	Superhet.	460 K.C.	1-6A7, 2-34, 1-6B7, 1-38	5V., Battery-Operated, Three Band	P.M.
"	152	Console	Superhet.	175 K.C.	2-34, 1-1A6, 1-30, 1-32, 1-33	6V., Battery-Operated	P.M.
"	153	Metal	Superhet.	175 K.C.	2-6D6, 1-6A7, 1-75, 1-76, 1-79	6V., Automobile Receiver, Class "B" output, motor-generator powered	E.M. 10 ohms
"	75	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 2000 ohms
"	76	Console	Superhet.	175 K.C.	1-34, 1-1A6, 1-6B7, 1-38	4V., Battery Operated	P.M.
"	77	Console	Superhet.	175 K.C.	1-1A6, 1-34, 1-32, 1-33	4V., Battery Operated	P.M.
"	244	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80	5V., A.C. Operated, Two Band	E.M. 2000 ohms
"	245	Console	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42 1-80	5V., A.C. Operated, Two Band	E.M. 2000 ohms
"	154	Console	Superhet.	175 K.C.	2-34, 1-1A6, 1-30, 1-32, 1-33	6V., Battery-Operated	P.M.
"	246	Console	Superhet.	460 K.C.	1-1C6, 2-34, 1-30, 1-32, 1-33	6V., Battery-Operated, Two Band	P.M.
"	247	Console	Superhet.	460 K.C.	3-34, 1-1C6, 1-30, 1-32, 1-33	7V., Battery-Operated, Three Band	P.M.
"	301A	Console	Superhet.	460 K.C.	3-6D6, 1-6A7, 1-6B7, 1-42, 1-6A6, 1-80	8V., A.C. Operated, Three Band	E.M. 850 ohms
"	"Radiolette" 30	Mantel	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms
1936	"Radiolette" 31	Mantel	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms
"	"Radiolette" 32	Mantel	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1936	Radiolette" 33	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80	5V., A.C. Operated, Two Band	E.M. 1600 ohms
"	"Radiolette" 35	Mantel	Superhet.	175 K.C.	1-1C6, 1-1C4, 1-1B5, 1-1D4	4V., Battery-Operated	P.M.
"	"Radiolette" 36	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-43	4V., D.C. Operated	E.M. 1000 ohms
"	155	Console	Superhet.	175 K.C.	1-6D6 1-6A7 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 2000 ohms
"	156	Console	Superhet.	175 K.C.	1-1C4 1-1C6, 1-6B7, 1-1D4	4V., Battery-Operated	P.M.
"	157	Console	Superhet.	175 K.C.	2-1C4, 1-1C6, 1-1B5, 1-1D4	5V., Battery-Operated	P.M.
"	158	Console	Superhet.	175 K.C.	2-6K7, 1-6A8, 1-6H6 1-6F5, 1-6F6, 1-80	7V., A.C. Operated Metal Valves	E.M. 2000 ohms
"	159	Console	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-43, 1-12Z3	5V., Universal A.C.-D.C.	E.M. 2000 ohms
"	248	Console	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80	5V., A.C. Operated, Two Band	E.M. 2000 ohms
"	249	Console	Superhet.	460 K.C.	2-6K7, 1-6A8, 1-6H6, 1-6F5, 1-6F6, 1-80	7V., A.C. Operated, Two Band, Metal Valves	E.M. 2000 ohms
"	250	Console	Superhet.	460 K.C.	3-1C4, 1-1C6, 1-1B5, 1-1D4	6V., Battery Operated, Two Band	P.M.
"	251	Console	Superhet.	460 K.C.	2-6K7, 1-6A8 1-6H6, 1-6F5, 2-6F6 1-6E5, 1-80	8V., A.C. Operated, Two Band, Metal Valves, Tuning Indicator	E.M. 1000 ohms
"	252	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-6B7, 1-43	5V., D.C. Operated, Two Band	E.M. 4500 ohms
"	253	Console	Superhet.	460 K.C.	3-1C4 1-1C6, 1-1B5, 1-30, 1-19	7V., Battery-Operated, Two Band, Class "B" Output	P.M.
"	254	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-6B7, 1-43	5V., 32 volt D.C. Operated, Two Band, Motor-Generator powered	E.M. 200 ohms
1937	"Radiolette" 37	Mantel	Superhet.	175 K.C.	1-6D6, 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms
"	"Radiolette" 38	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6 1-6B7, 1-42, 1-80	5V., A.C. Operated, Two Band	E.M. 1600 ohms
"	"Radiolette" 39	Mantel	Superhet.	460 K.C.	1-1C6, 1-1C4, 1-1K6, 1-1D4	4V., Battery-Operated	P.M.
"	"Radiolette" 42B	Console	Superhet.	460 K.C.	1-1C6, 1-1C4, 1-1K6, 1-1D4	4V., Battery-Operated	P.M.
"	"Radiolette" 40	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-43	4V., D.C. Operated, Two Band	E.M. 1000 ohms
"	"Radiolette" 43	Console	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-43	4V., D.C. Operated, Two Band	E.M. 1000 ohms
"	"Radiolette" 42V	Console	Superhet.	460 K.C.	1-1C6, 1-1C4, 1-1K6, 1-1D4	4V., Vibrator Operated	P.M.
"	160	Console	Superhet.	460 K.C.	1-6D6 1-6A7, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 2000 ohms

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1937	161	Console	Superhet.	460 K.C.	2-1C4, 1-1C6, 1-1K6, 1-1D4	5V., Vibrator-Battery Operated (convertible)	P.M.
"	255	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-6B7, 1-42, 1-80	6V., A.C. Operated, Two Band	E.M. 2000 ohms
"	256	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-6B7, 1-42, 1-80, 1-6G5	6V., A.C. Operated, Three Band, Tuning Indicator	E.M. 2000 ohms
"	257	Console	Superhet.	460 K.C.	2-6K7, 2-6L7, 2-6H6, 1-6J7, 1-6L6, 1-80, 1-6G5	9V., A.C. Operated, Three Band, Tuning Indicator, Muting System	E.M. 650 ohms
"	258	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-6B7, 1-43, 1-6G5	5V., D.C. Operated, Three Band, Tuning Indicator	E.M. 4500 ohms
"	259	Console	Superhet.	460 K.C.	2-1C4, 1-1C6, 1-1K6, 1-1D4	5V., Vibrator-Battery Operated (Convertible), Two Band	P.M.
"	260	Console	Superhet.	460 K.C.	3-1C4, 1-1C6, 1-1K6, 1-1K4, 1-19	7V., Vibrator-Battery Operated (Convertible), Three Band, Class "B" Output	P.M.
"	261	Console	Superhet.	460 K.C.	2-6D6, 1-6A7, 1-6B7, 1-43, 1-6G5	5V., 32 Volt D.C. Vibrator Operated, Three Band	E.M. 200 ohms
"	262	Console	Superhet.	460 K.C.	2-6K7, 2-6L7, 2-6H6, 2-6L6, 1-6N7, 1-6J7, 1-5Z3, 1-6G5	11V., A.C. Operated, Three Band, Muting System, Tuning Indicator, Push-Pull Output	E.M. 500 ohms
"	401	Metal	Superhet.	175 K.C.	2-6K7, 1-6A8, 1-6Q7, 1-6F6, 1-6X5	6V., Automobile Receiver, Vibrator Operated, Internal Loudspeaker, 6 or 12 volt	E.M. 5 ohms (6V), E.M. 20 ohms (12V)
"	402	Metal	Superhet.	175 K.C.	2-6K7, 1-6A8, 1-6Q7, 1-6F6, 1-6X5	6V., Automobile Receiver, Vibrator Operated, External Loudspeaker, 6 or 12 volt	E.M. 5 ohms (6V), E.M. 20 ohms (12V)
"	403	Metal	Superhet.	175 K.C.	2-6K7, 1-6A8, 1-6Q7, 1-6F6, 1-6X5	6V., Automobile Receiver, Vibrator Operated, External Loudspeaker, 12 volt	E.M. 20 ohms
1938	48	Mantel	Superhet.	460 K.C.	1-6A7, 1-6B7, 1-42, 1-80	4V., A.C. Operated	E.M. 1600 ohms
"	49	Mantel	Superhet.	460 K.C.	1-1C6, 1-1D5G, 1-1K6, 1-1D4	4V., Battery-Operated	P.M.
"	164	Console	Superhet.	460 K.C.	1-1C6, 1-1D5G, 1-1K6, 1-1D4	4V., Vibrator-Battery Operated (Convertible)	P.M.
"	50	Mantel	Superhet.	460 K.C.	1-1C6, 2-1D5G, 1-1K6, 1-1D4	5V., Battery-Operated, Two Band	P.M.
"	165	Console	Superhet.	460 K.C.	1-1C6, 2-1D5G, 1-1K6, 1-1D4	5V., Vibrator-Battery Operated (Convertible), Two Band	P.M.
"	51	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80	5V., A.C. Operated	E.M. 1600 ohms
"	162	Console	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80, 1-6U5	5V., A.C. Operated, Tuning Indicator	E.M. 1600 ohms
"	52	Mantel	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80, 1-6U5	5V., A.C. Operated, Two Band	E.M. 1600 ohms

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FREQU.	VALVES	DETAILS	LOUDSPEAKER
1938	163	Console	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-42, 1-80, 1-6U5	5V., A.C. Operated, Two Band, Tuning Indicator	E.M. 1600 ohms
"	53	Mantle	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-43, 1-302 Barretter	4V., D.C. Operated, Two Band	E.M. 1000 ohms
"	166	Console	Superhet.	460 K.C.	1-6A7, 1-6D6, 1-6B7, 1-43, 1-302 Barretter	4V., D.C. Operated, Two Band, Tuning Indicator	E.M. 4500 ohms
"	167	Console	Superhet.	460 K.C.	1-6U7G, 1-6A8G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., A.C. Operated, Tuning Indicator	E.M. 1580 ohms
"	263	Console	Superhet.	460 K.C.	1-6U7G, 1-6A8G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., A.C. Operated, Two Band, Tuning Indicator	E.M. 1580 ohms
"	264	Console	Superhet.	460 K.C.	2-6K7, 3-6J7, 1-6L7, 1-6H6, 1-6V6G, 1-5Z3, 1-6U5	9V., A.C. Operated, Three Band, Automatically Motor Tuned, Metal Valves, A.F.C. Tuning Indicator	E.M. 1000 ohms
"	265	Console	Superhet.	460 K.C.	2-1D5G, 1-1C7G, 1-1F7G, 1-1E5G, 1-1J6G	6V., Vibrator-Battery Operated (Convertible), Two Band, Class "B" output.	P.M.
"	266	Console	Superhet.	460 K.C.	2-6U7G, 1-6A8G, 1-6H6G, 1-6J7G, 1-6V6G, 1-5Y3G, 1-6U5	7V., A.C. Operated, Three Band, Tuning Indicator	E.M. 1300 ohms
"	267	Console	Superhet.	460 K.C.	3-1D5G, 1-1C7G, 1-1F7G, 1-1E5G, 1-1J6G	7V., Vibrator-Battery Operated (Convertible), Three Band	P.M.
"	268	Console	Superhet.	460 K.C.	2-6U7G, 1-6A8G, 1-6G8G, 1-43, 1-302 Barretter, 1-6U5	5V., D.C. Operated, Three Band, Tuning Indicator	E.M. 4500 ohms
"	304	Radiogram	Superhet.	460 K.C.	1-6U7G, 1-6A8G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., Phono-Radio, A.C. Operated, Tuning Indicator	E.M. 1580 ohms
"	305	Radiogram	Superhet.	460 K.C.	1-6U7G, 1-6A8G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., Phono-Radio, A.C. Operated, Two Band, Tuning Indicator	E.M. 1580 ohms
"	306	Radiogram	Superhet.	460 K.C.	2-6U7G, 1-6A8G, 1-6H6G, 1-6J7G, 1-6V6G, 1-5Y3G, 1-6U5	7V., Phono-Radio, A.C. Operated, Three Band, Tuning Indicator	E.M. 1300 ohms
"	307	Radiogram	Superhet.	460 K.C.	2-6K7, 3-6J7, 1-6L7, 1-6H6, 1-6V6G, 1-5Z3, 1-6U5	9V., Automatic Record Changing Phono-Radio, A.C. Operated, Metal Valves, A.F.C. Tuning Indicator	E.M. 1000 ohms
"	308	Radiogram	Superhet.	460 K.C.	2-1D5G, 1-1C7G, 1-1F7G, 1-1E5G, 1-1J6G	6V., Phono-Radio Vibrator-Battery Operated (Convertible), Two Band, Class "B" output	P.M.
"	48G	Mantel	Superhet.	460 K.C.	1-6A8G, 1-6G8G, 1-6F6G, 1-5Y3G	4V., A.C. Operated	E.M. 1600 ohms

COMPLETE LIST RADIOLA RECEIVERS 1925-1938

YEAR	MODEL	CABINET	CIRCUIT	I.F. FRE- QUENCY	VALVES	DETAILS	LOUDSPEAKER
1938	49G	Mantel	Superhet.	460 K.C.	1-1C7G, 1-1D5G, 1-1K7G, 1-1L5G	4V., Battery-Operated	P.M.
"	49GV	Mantel	Superhet.	460 K.C.	1-1C7G, 1-1D5G, 1-1K7G, 1-1L5G	4V., Vibrator-Operated	P.M.
"	50G	Mantel	Superhet.	460 K.C.	1-1C7G, 2-1D5G, 1-1K7G, 1-1L5G	5V., Battery-Operated, Two Band	P.M.
"	50GV	Mantel	Superhet.	460 K.C.	1-1C7G, 2-1D5G, 1-1K7G, 1-1L5G	5V., Vibrator-Operated	P.M.
"	51G	Mantel	Superhet.	460 K.C.	1-6A8G, 1-6U7G, 1-6G8G, 1-6F6G, 1-5Y3G	5V., A.C. Operated	E.M. 1600 ohms
"	52G	Mantel	Superhet.	460 K.C.	1-6A8G, 1-6U7G, 1-6G8G, 1-6F6G, 1-5Y3G	5V., A.C. Operated, Two Band	E.M. 1600 ohms
"	53G	Mantel	Superhet.	460 K.C.	1-6A8G, 1-6U7G, 1-6G8G, 1-43, 1-302 Barretter	4V., D.C. Operated, Two Band	E.M. 1000 ohms
"	170	Console	Superhet.	460 K.C.	1-6K8G, 1-6U7G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., A.C. Operated, Tuning Indicator	E.M. 1580 ohms
"	171	Console	Superhet.	460 K.C.	1-6K8G, 1-6U7G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., A.C. Operated, Automatically tuned, Tuning Indicator	E.M. 1580 ohms
"	172	Console	Superhet.	460 K.C.	1-6A8G, 1-6U7G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., A.C. Operated, Two Band, Tuning Indicator	E.M. 1580 ohms
"	173	Console	Superhet.	460 K.C.	1-6K8G, 1-6U7G, 1-6G8G, 1-6F6G, 1-5Y3G, 1-6U5	5V., A.C. Operated, Two Band, Auto- matically Tuned, Tuning Indicator.	E.M. 1580 ohms
"	174	Console	Superhet.	460 K.C.	1-1C7G, 1-1D5G, 1-1K7G, 1-1L5G	4V., Vibrator-Battery Operated (Con- vertible)	P.M.
"	175	Console	Superhet.	460 K.C.	1-1C7G, 2-1D5G, 1-1K7G, 1-1L5G	5V., Vibrator-Battery Operated (Con- vertible), Two Band	P.M.
"	176	Console	Superhet.	460 K.C.	1-6K8G, 1-6U7G, 1-6G8G, 1-43, 1-302 Barretter	4V., D.C. Operated, Two Band, Tuning Indicator	E.M. 4500 ohms

