

The logo consists of the word "GRUNDIG" in a bold, white, sans-serif font, centered within a white, horizontally-oriented oval shape. This oval is set against a solid black rectangular background.

GRUNDIG

**Einstellprogramm
für LCD-Uhr**

**Setting programme
for the LCD clock**

**Programme de réglage
pour l'horloge LCD**

**Programma di regolazione
dell'orologio LCD**

**Instelprogramma
voor de LCD-klok**

After fitting or changing the batteries, arbitrary numbers appear.



FUNCT. Function selection (time/date) Entry of data

SELECT. Selecting the position, which has to be set

Press the button as long (indication advances in $\frac{1}{2}$ second rhythm), or as often, until the desired indication is reached.

Press once
Indication blinks in $\frac{1}{2}$ second rhythm

1) By actuating the "SELECT." button after the minutes have been set it is possible to start the clock **exactly to the second** (e. g. by means of radio or TV time check).

2) If the indication "time" is desired at once, then the "FUNCT." button must be pressed **4 times**. The appearing symbols have no function in this unit.

Attention: After adjustment has been completed, the "SELECT." button must be pressed repeatedly until no sign is blinking.

Setting the clock time

FUNCT. S1	SELECT. S2	Indication	Explanation
—	—	10:25 08	Initial state: arbitrary time indication
—	<input checked="" type="button"/>	10:25 10	Ready for setting the hours
<input type="button"/>	—	22:25 35	Setting hours, clock function not interrupted
—	<input checked="" type="button"/>	22:25 40	Ready for setting the minutes, clock function not interrupted
<input type="button"/>	—	22:06 00	Setting minutes, clock function interrupted, seconds at zero
—	<input checked="" type="button"/>	22:06 00	Setting process concluded, clock function started, indication, "time" 1)

Setting the date (week-day, calendar day, month) (German week-day letters)

—	—	22:06 30	Initial state: "time"
<input checked="" type="button"/>	—	MO 8 2	Indication: date
—	<input checked="" type="button"/>	MO 8 2	Ready for setting the week-day
<input type="button"/>	—	DO 8 2	Setting week-day
—	<input checked="" type="button"/>	DO 8 2	Ready for setting the calendar day
<input type="button"/>	—	DO 12 2	Setting calendar day
—	<input checked="" type="button"/>	DO 12 2	Ready for setting the month
<input type="button"/>	—	DO 12 11	Setting month
—	<input checked="" type="button"/>	DO 12 11	Setting concluded, indication "date". Changes after approx. 30 secs. back to indication "time". 2)