

Stückliste zum Schaltbild 580/I

SABA 455 WK

Nr.	Widerstände	Bestell-Nr.	Nr.	Kondensatoren	Bestell-Nr.
1	Ma. 500 K Ohm	216/9	39	25 pF	462/6
2	Ma. 200 "	580/148	40	15 "	462/4
3	Ma. 50 K "	181/26	41	60 000 "	} 442/86
4	Dr. 250 "	382/IV	42	30 000 "	
5	Ma. 50 K "	344/21	43	0,1 µF	442/71
6	Ma. 30 K "	370/105	44	50 pF	462/11
7	Ma. 200 "	580/148	45	0,1 µF	442/78
8	Ma. 1 K "	360/98	46	15 pF	462/4
9	Ma. 1 M "	112/68	47	440 "	472/36
10	Ma. 1,5 M "	301/100	48	187 "	472/33
11	Ma. 200 "	580/148	49	10 "	462/3
12	Dr. 300 "	382/V	50	2 500 "	} 442/87
13	Ma. 0,3 M "	213/30	51	7 500 "	
14	Ma. 0,2 M "	138/29	52	0,1 µF	442/78
15	Ma. 1,5 M "	301/100	53	220 pF	472/35
16	Ma. 0,1 M "	138/28	54	220 "	472/35
17	Ma. 1 M "	112/68	55	220 "	472/35
18	Ma. Potentiom. 1,5 M "	560/52	56	0,1 µF	442/77
19	Ma. 1 K "	360/98	57	100 pF	462/12
20	Ma. 50 K "	344/21	58	0,1 µF	442/77
21	Dr. 1 K "	382/X	59	100 pF	462/12
22	Ma. 0,3 M "	213/30	60	220 "	472/35
23	Ma. 100 K "	138/28	61	220 "	472/35
24	Ma. 30 K "	332/122	62	0,1 µF	442/78
25	Ma. 1 M "	112/68	63	3 000 pF	442/53
26	Ma. 100 K "	138/28	64	20 000 "	442/66
27	Ma. 1 K "	360/98	65	0,1 µF	442/78
28	Ma. Potentiom. 0,6 M "	560/52	66	8 "	452/3
29	Ma. 0,5 M "	216/9	67	0,5 "	580/82
30	Ma. 0,5 M "	216/9	68	5 000 pF	442/33
31	Ma. 0,2 M "	138/29	69	20 000 "	442/66
32	Dr. 100 "	382/XV	70	0,5 µF	580/82
33	Dr. 150 "	382/XIV	71	1 000 pF	442/58
34	Ma. 1 K "	360/98	72	200 "	442/54
35	Ma. 0,1 M "	138/28	73	25 µF	452/6
			74	3 000 pF	442/53
			75	0,01 µF	453/36
			76	0,01 "	453/36
			77	16 "	580/81
			78	16 "	580/81
			79	10 000 pF	442/63
			80	0,1 µF	442/71
			85	200 pF	442/54
			86	500 "	442/57
81	Verschiedenes: Soffittenlampe 6,3 V 0,3 Amp.	580/111			
82	Soffittenlampe 6,3 V 0,3 Amp.	580/111			
83	Sicherung 0,7 Amp.	563/37			
84	Sicherung 1,4 Amp.	563/38			

455

Ma. = Massewiderstand Dr. = Drahtwiderstand